

## **11 - Adjusting Printer Settings**

Written By: Eric Sutter

0000000						
nsole Functions Tools Advan	ced /	About				
≝   ₽ © <b>२</b>   ⊕ ୭ (	120	// A? 🌾 🌾 🕊	2 🗳 🖄	: 🖡 🖬 🛱 🗄 (	Group: All	
inters Printer	-	Interface	Model	Version	Serial No.	Mil
GSS-LABEL-PTR-I	<b>(··)</b>	10.121.80.117	GSS-LABEL-P	B1.25 EZD TCF		0.04
PS-8104AF	(··)	10.121.80.83	1X200	A2.12 EZD		0.07
GSS-LABEL-PTR-L	Ψ	USB	GSS-LABEL-P	B0.98.002 EZC		0.00
	Insole Functions Tools Advant Functions Functi	Insole Functions Tools Advanced A Functions Tools Advanced A Functions Tools Advanced A Functions Tools Advanced A Solution Statement Advanced A Functions Tools Advanced A Functions Tools Advanced A Functions Tools Advanced A Function Statement Advanced A	Functions Tools Advanced About   Image: Second state   Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state   Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state   Image: Second state	Functions Tools Advanced About   Image: Second state   Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state Image: Second state   Image: Second state Image: Seco	Functions Tools Advanced About   Image: State of the	Functions Tools Advanced About   Image: Printer

This document was generated on 2025-07-22 06:36:53 PM (MST).

## Step 1 — Connecting & Initializing

			T.							Advar ∂C ∜	nced / ∂≣	About //□ A? XE KE ♥	• 🗈 🗳 🎗	<u>a</u> ] = ♣	að @ i Group: All		• •			
		INC	Console							r		Interface	Model	Ver	sion Serial No.	Mi	ileage (Km)	Batt. Capacity	Batt. Life	
		V1	.0.59.1							R-I	<i>(</i> ·· <i>)</i>	10.121.80.117	GSS-LABE	Add Printers		× 04	110			23/
ſ	🛞 TSC	Conso	le								<b>(··)</b>	10.121.80.83	TX200			07	717			28/
	KUUN	E Fu	inctions Tools Advance	d	About					TR	Ψ	USB	Alpha-40L	● JSB	~	oc 0	089			16/
	5	3	₽© <b>₽</b>   <b>₽</b> ℃@	E	/ ▲ ▲ ▲ ●	1 🗃 🖄 1		Group: All	- 10	R-I	Ψ	USB	GSS-LABE	О сом	COM1 ~	¢	428			28/
	[Ad	d Printe	rs Printer		Interface	Model	Version	Serial No.	Mileage (K					⊖ LPT	LPT1 ~	- 1				
		9	GSS-LABEL-PTR-I	<b>«··</b> »	10.121.80.117	GSS-LABEL-P	B1.25 EZD TCF		0.0410					O Netwo	rk	- 1				
		9	PS-8104AF	<b>«··</b> »	10.121.80.83	TX200	A2.12 EZD		0.0717							- 1				
		9	GSS MOBILE PTR	ψ	USB	Alpha-40L	B0.98.002 EZC		0.0089						ОК					
			GSS-LABEL-PTR-I	÷	USB	GSS-LABEL-P	B1.25 EZD TCF		0.0428					-		E				

- Make sure the printer is connected via USB before powering the printer on. To see how to connect it via USB click HERE and to see how to confirm it's connection, click HERE.
- Launch the GSS Certified Printer Tool software.
  - If you do not have it downloaded, download <u>HERE</u>.
- Select "Add Printers" in GSS Certified Printer Tool if your printer is not yet connected. If it is, skip this step.
  - Make sure USB is selected by clicking the bullet point next to 'USB," shown by the orange box.
  - Select the drop down menu, shown by the blue box, to find and select the printer
    - If it does not show up, try selecting the 'refresh USB list' button shown by the pink arrow. If it still does not appear, try turning off the printer, waiting a moment for it to fully power off, then powering it back on and repeating this step.
  - Select 'OK.'

This document was generated on 2025-07-22 06:36:53 PM (MST).

## Step 2 — Navigating to Adv. Printer Settings

Biological     © TSC Console     Printers   Functions     For Console     Printers   Functions     I D O O I O D D D A F O O O O O O D D A F O O O O O O O O O O O O O O O O O O	Printer Configuration   X     Printer Configuration   Printer Configuration     Printer Configuration   Printer Configuration     Adverse   Calcolation     Calcolation   Read Read Read Read Read Read Read Read	Print   Comparison   X     Print   Comparison   Final   Comparison   X     Print   Comparison   Final   Comparison   Comparison   Comparison     Print   Comparison   <
Status   Print   Instruction   Model   Version   Serval Mo.   Metage (m)     ♥   0.55-URELP, P. 10 524 0.90   0.554 9.00   0.549 9.00   0.024 9.00   0.024 9.00   0.024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.0024 9.00   0.012 1.00   0.012 1.00   0.012 1.00   0.012 1.00   0.012 1.00   0.012 1.00   0.012 1.00   0.0024 9.00   0.0024 9.00   0.012 9.00   0.012 9.00   0.012 9.00   0.012 9.00   0.012 9.00   0.012 9.00   0.012 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00   0.014 9.00 <th>● 10 ● 10 ● 10 ● 10 ● 10 ● 10 ● 10 ● 10</th> <th>1000000000000000000000000000000000000</th>	● 10 ● 10 ● 10 ● 10 ● 10 ● 10 ● 10 ● 10	1000000000000000000000000000000000000

- Double click the printer name, to open up the Printer Configuration Menu.
- In the Printer Configuration Menu select the 'Emulation' tab.
- Click on 'Get' in the bottom right hand of the pop up, shown by the orange box.
  - The fields will now populate with information given from the printer, shown by the green box.

rinter Configuration Emul	ation TPH Care Smart Battery	Unit: inch 🗸
Z D		
Darkness:	16 0 ~ 30	
Print Speed:	2	
Tear Off Pos:	0 -120 ~ 120	
Print Mode:	Tear Off 🗸 🗸	
Print Width:	812 dot	
Control Prefix:	~	
Format Prefix:	٨	
Delimiter Char:	,	
Media Power Up:	Calibration	
Head Close:	Calibration ~	
Label Top:	0 -120 ~ 120	
Left Position:	0 -9999 ~ 9999	

## Step 3 — Changing the Darkness

- The Darkness is how dark your printer prints labels.
- The default is preloaded and it is recommended it remains about the same darkness as it came as.
- To change it, click in the text box and enter a number between 0 and 30.
  - The closer the number is to 0, the lighter your prints will be.
  - The closer the number is to 30, the darker your prints will be.

This document was generated on 2025-07-22 06:36:53 PM (MST).