




CH28-A - 360 Servo Button Slow Spin

Connect a 360° Servo to a Bit Board and control it with a Pushbutton and code.

Written By: Pete Prodoehl



INTRODUCTION

Connect a 360° Servo to a Bit Board and control it with a Pushbutton and code.

We'll explore code to control the movement of a continuous rotation (360 degree) servo motor using a button.



TOOLS:


- [Computer](#) (1)
- [Scissors](#) (1)



PARTS:


- [Crazy Circuits Bit Board](#) (1)
- [micro:bit](#) (1)
- [Brick Compatible 360 Degree Servo](#) (1)
- [Standard Pushbutton Chip](#) (1)

Step 1 — Connect the 360° Servo and Pushbutton




- The **360 Degree Servo Motor** has a 3-wire connector on the end that can plug directly into the pins on the back of the Bit Board.
- Make sure the **Orange Wire** is closest to the number **13** for the **Pin 13** column.
- Then the **Brown Wire** should be closest to the micro:bit (in the - row) and the **Red Wire** will be in the middle (the **+5v** row).
- Connect the Button with **Maker Tape**, with one side to **Pin 5** and the other to **GND**.

Step 2 — Load the Code




- If you've never used a micro:bit before you'll want to check out this guide: [Bit Board V2 Setup and Use](#)
- We're going to load the following code for our **360 Servo Button Slow Spin** program: https://makecode.microbit.org/_Mp0MW2EKP...
- We'll get our button all set in the start block by setting it to **up** so when the button is shorted to GND (ground) or "pulled down" we can read the state.
- In the forever block we check for the button to be pressed, and when that happens we spin the servo on **Pin 13** at a speed of **15%**.
- When the button is not being pressed (and held down) we'll stop the servo with the turn off motor statement.

Step 3 — Test it Out!



- Once the code is loaded it should start running immediately, but nothing will happen until we press and hold the button!
- ⓘ You can power the micro:bit via the USB cable you used to load the code, but now that we are using servos we recommend using a battery pack plugged into the Bit Board.
- ★ The [Blue Pins](#) on the Bit Board provide extra power (5 volts instead of 3 volts) by **boosting the voltage** coming from the battery pack. This helps improve servo performance, especially with multiple servos.
- When you press and hold the button the servo will spin slowly. When you release the button the servo will stop moving.

Step 4 — Follow Along



- Follow along with our recorded Live Stream!
- ① You can watch the full video of us walking through this project, along with explaining and exploring the code:
<https://youtube.com/live/HcgJJ8a2K>
[I](#)