




CH28-B - 360 Servo Button Slower Spin

Connect a 360° Servo to a Bit Board and control it with a Pushbutton and code.

Written By: Pete Prodoehl



INTRODUCTION

Connect a 360° Servo to a Bit Board and control it with a Pushbutton and code.

We'll explore code to control the movement of a continuous rotation (360 degree) servo motor using a button.



TOOLS:


- [Computer](#) (1)
- [Scissors](#) (1)



PARTS:


- [Crazy Circuits Bit Board](#) (1)
- [micro:bit](#) (1)
- [Brick Compatible 360 Degree Servo](#) (1)
- [Standard Pushbutton Chip](#) (1)

Step 1 — Connect the 360° Servo and Pushbutton




- The **360 Degree Servo Motor** has a 3-wire connector on the end that can plug directly into the pins on the back of the Bit Board.
- Make sure the **Orange Wire** is closest to the number **13** for the **Pin 13** column.
- Then the **Brown Wire** should be closest to the micro:bit (in the - row) and the **Red Wire** will be in the middle (the **+5v** row).
- Connect the Button with **Maker Tape**, with one side to **Pin 5** and the other to **GND**.

Step 2 — Load the Code




- If you've never used a micro:bit before you'll want to check out this guide: [Bit Board V2 Setup and Use](#)
- We're going to load the following code for our **360 Servo Button Slower Spin** program: https://makecode.microbit.org/_Hc1bkgAwY...
- We'll get our button all set in the start block by setting it to **up** so when the button is shorted to GND (ground) or "pulled down" we can read the state.
- We'll also set our **speedVal** variable to **15**, which should get the motor moving very slowly.
- While the motor speed can be set between **0** and **100** there's a certain amount of "speed" that needs to be applied to get the motor moving, and this code will help us determine that number.
- In the forever block we check for the button to be pressed, and with each press we change the **speedVal** by -1.

Step 3 — Test it Out!



- Once the code is loaded it should start running immediately.
- ① You can power the micro:bit via the USB cable you used to load the code, but now that we are using servos we recommend using a battery pack plugged into the Bit Board.
- ★ The [Blue Pins](#) on the Bit Board provide extra power (5 volts instead of 3 volts) by **boosting the voltage** coming from the battery pack. This helps improve servo performance, especially with multiple servos.
- The servo will start spinning very slowly.
- Press the button once and the motor will move slower. It will only be 1% slower, so you may not notice it.
- Wait a few seconds, and then press the button again. Repeat this process until the motor stops moving.

Step 4 — Follow Along



- Follow along with our recorded Live Stream!
- ⓘ You can watch the full video of us walking through this project, along with explaining and exploring the code:
<https://youtube.com/live/HcgJJ8a2K>
[I](#)